

# CLASSIC

## STEP DOWN TRANSFORMERS

MODELS 95T-16/16P40



**Model 16P40**

**Model 95T-16** Shown attached to standard junction box.

### FUNCTION

The step-down transformers provided by Lencore are industry listed by UL and/or CSA for electrical safety. For masking only, Model #16P40 can handle up to 33 masking units. Our larger transformer, Model #95T-16 can handle up to 78 masking units. Where paging is incorporated, the 95T-16 handles approximately 33 masking units and the 16P40, 12 units. The transformers step down from 120 AC voltage to 16v AC voltage. One 95 T-16 model can be attached to a standard junction box. Please note: It is recommended that final hookup of transformer to building power always be performed by an electrician (For 95T-16 only).

### SPECIFICATIONS

MODEL#	95T-16	16P40
TRANSFORMER SPECIFICATIONS:	16V/95VA	16V/40VA
SIZE:	4 1/4" X 4 1/4" X 4"	2 1/2" X 3 3/8" X 2"
POWER RATING:	95VA	40VA
POWER REQUIREMENT:	120v AC, 60 Hz	120v AC, 60 Hz
FUSE:	6-Amp Reset Circuit Breaker	4-AMP Resettable