

i.Net / Classic

MIXER AMPLIFIER 35W & 60W

MODELS APFR-M35/APFR-M60



DESCRIPTION

The APFR-M35 & APFR-M60 are designed to operate as the front end to any commercial audio system in background music (BGM), foreground music, paging applications and more. The mixer amplifiers feature 5-channels and a power rating of 60 watts, with 2-zone operation allowing for separate programming in 2 discrete zones. The front panel features an intuitive set of controls with level dials for each channel. The rear is fitted with removable euroblock connectors and DIP switches for easy programming.

FEATURES AND CAPABILITIES

- + Compact five channel Mixer-Amplifier for paging, background/ foreground music distribution and music/messaging-on-hold.
- + All inputs/outputs with removable terminal blocks allow quick and easy installation.
- + Any of five inputs assignable to MOH/ZONE 2 output.
- + Phantom Power (+ 24V DC) incorporated for MIC input.
- + Rear panel-mounted DIP switches allow easy configuring of settings.
- + Tamper-proof, front-panel bass and treble controls are recessed to protect their settings.
- + Incorporates Remote volume control connection.
- + Thermal protection circuitry prevents potential damage from excessive heat build-up.
- + UL/CUL listed.

i.Net / Classic

MIXER AMPLIFIER 35W & 60W

MODELS APFR-M35/APFR-M60

DIMENSIONS

- + 10.39 × 3.71 × 10.52" (264 x 94.3 x 267.3mm)

WEIGHT

- + 5.3

kg

RATED OUTPUT

- + APFR-M35- 35 W
- + APFR-M60- 60 W

POWER CONSUMPTION

- + APFR-M60- 163 W (rated output), 80 W (based on cULus standards) Power Source: 120 VAC, 60Hz
- + APFR-M35- 94 W (rated output), 50 W (based on cULus standards) Power Source: 120 VAC, 60H

FREQUENCY RESPONSE

- + 50Hz - 20kHz

INPUT

- + Mic: -60dB, 600 Ω, electronically balanced, removable terminal block.
Line 1: -10dB/ TEL: -20dB
Line 1/TEL selectable, 10 kΩ, electronically balanced, removable terminal block
Line 2, 3: -10dB, 10 kΩ, unbalanced, removable terminal block and RCA jacks Module

OUTPUT

- + Speaker: 4 Ω, 25V (10 Ω), 70V (83 Ω), balanced, removable terminal block MOH: 0dB, 600 Ω, balanced, removable terminal block Line: 0dB, 600 Ω, unbalanced, removable terminal block

OUTPUT REGULATION

- + 2dB or less, no load to full load (1k Hz)

S/N RATIO

- + Mic/Line 1: 60 dB or more/Line 2, 3: 80 dB or more

MUTING

- + Manual mute / automatic mute

POWER SOURCE

- + 20 V AC, 60 Hz

TOTAL HARMONIC DISTORTION

- + 0.5% or less, at 1 kHz, rated output

tone control

- + Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz

CONTROL

- + Mic gain control, Line 1/TEL gain control, Line 2 gain control, Line 3 gain control, Module gain control, Bass tone control, Treble tone control, MOH out gain control, Mute control (Manual mute), Remote volume control, Mute sense control, Line 1/TEL selector switch, Phantom power switch (Mic), Auto mute switch (Mic, Line 1/TEL, Module), Mute receive switch (Mic, Line 1/TEL, Line 2, 3, Module), MOH assign switch (Mic, Line 1/TEL, Line 2, 3, Module), Power ON/OFF switch

INDICATORS

- + Power LED, Signal level LED, Peak LED

OPERATING TEMPERATURE

- + Operating Temperature: 0°C to 40 °C (32°F to 104 °F)
Operating Humidity: 35% to 80% RH (no condensation)

OPERATING HUMIDITY

- + 35% to 80% RH (no condensation)

FINISH

- + Panel: ABS resin, black/Case: Steel plate, black, paint

PHANTOM POWER

- + On/Off switch for Mic, +24V DC

SIGNAL TO NOISE RATIO

- + Mic: 60 dB or more, Line 1/TEL, Line 2, 3, Module: 75 dB or more (Band Pass: 20 Hz - 20 kHz, Tone Controls: Centered)